

# Mixers

## Analogue Mixers

### MXR-120PRO

Order No. 0200620



**Professional 12-channel audio mixer**, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 8 mono input channels with gain control, 3-way equalizer and pan pot
- 2 stereo input channels with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 different DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display



Model	MXR-120PRO
Mic input	0.6 mV, bal. 8 x XLR
Line input	80 mV (stereo), 2 x 6.3 mm jack L/R 7 mV (mono), 8 x 6.3 mm jack
Aux input	340 mV, 1 x 6.3 mm jack L/R
Master output	760 mV, 1 x 6.3 mm jack L/R
Effect send	9 V, 1 x 6.3 mm jack
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 75 dBA
Equalizer bass	±15 dB/80 Hz
Equalizer midrange	±15 dB/2.5 kHz
Equalizer treble	±15 dB/12 kHz
Power supply	~ 230 V/50 Hz/30 VA
Dimensions	484 x 93 x 320 mm
Weight	4.4 kg

### MXR-80PRO

Order No. 0200530



**Professional 8-channel audio mixer**, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 4 mono input channels with gain control, 3-way equalizer and pan pot
- 2 stereo input channels with 3-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 different DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display



Model	MXR-80PRO
Mic input	0.6 mV, bal. 4 x XLR
Line input	80 mV (stereo), 2 x 6.3 mm jack L/R 7 mV (mono), 4 x 6.3 mm jack
Aux input	340 mV, 1 x 6.3 mm jack L/R
Master output	760 mV, 1 x 6.3 mm jack L/R
Effect send	9 V, 1 x 6.3 mm jack
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 75 dBA
Equalizer bass	±15 dB/80 Hz
Equalizer midrange	±15 dB/2.5 kHz
Equalizer treble	±15 dB/12 kHz
Power supply	~ 230 V/50 Hz/25 VA
Dimensions	364 x 93 x 320 mm
Weight	3.4 kg