

Mixers

Analogue Mixers

MXR-6

Order No. 0200280



6-channel audio mixer, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 4 mono input channels with gain control, 2-way equalizer and pan pot
- 2 stereo input channels with 2-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 different DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display
- Power is provided via USB or enclosed power supply



Model	MXR-6
Mic input	2 mV, bal. 4 x XLR
Line input	100 mV (stereo), 2 x 6.3 mm jack L/R 60 mV (mono), 2 x 6.3 mm jack
Aux input	400 mV, 1 x 6.3 mm jack L/R
Master output	500 mV, 1 x 6.3 mm jack L/R
Effect send	4.4 V, 1 x 6.3 mm jack
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 83 dBA
Equalizer bass	±15 dB/80 Hz
Equalizer treble	±15 dB/12 kHz
Power supply	USB or encl. power supply
Dimensions	308 x 53 x 205 mm
Weight	1.9 kg

MXR-4

Order No. 0200250



4-channel audio mixer, with DSP effect unit, integrated MP3 player and Bluetooth receiver.

- Integrated USB audio interface (will be identified and addressed as an external sound card)
- Full-duplex USB port (allows for simultaneous recording and reproduction) for reproduction of digital audio data from a PC and for recording mixings onto a PC
- 2 mono input channels with gain control, 2-way equalizer and pan pot
- 1 stereo input channel with 2-way equalizer and balance control
- MP3 player
- USB interface
- Bluetooth receiver
- 16 different DSP effects
- Adjustable aux return input and FX send output
- +48 V phantom power, can be activated as required
- Adjustable headphone output
- Stereo LED level display
- Power is provided via USB or supplied power supply



Model	MXR-4
Mic input	2 mV, bal. 2 x XLR
Line input	100 mV (stereo), 2 x 6.3 mm jack L/R 60 mV (mono), 2 x 6.3 mm jack
Aux input	400 mV, 1 x 6.3 mm jack L/R
Master output	500 mV, 1 x 6.3 mm jack L/R
Effect send	4.4 V, 1 x 6.3 mm jack
Headphones	≥ 8 Ω, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.03%
S/N ratio	> 83 dBA
Equalizer bass	±15 dB/80 Hz
Equalizer treble	±15 dB/12 kHz
Power supply	USB or encl. power supply
Dimensions	228 x 53 x 205 mm
Weight	1.4 kg